

8 Channels CWDM Mux/Demux + Expansion Port (without Monitor port)

Description

The adjacent channels of CWDM use parallel beams to cascade in free space instead of using optical fibers. Without the fiber used in cascade, the size of CWDM package can reach 54x25x7mm, which is about 3 times smaller than that of standard DWDM package.

CWDM optical module is widely used in the fields of coarse wavelength division multiplexing system, PON network, CATV link, telecommunication network, enterprise network, metropolitan area network WDM system, 4G/5G communication mobile system, 100G solution, access network, metropolitan area network WDM system, optical fiber tools and so on.

Feature

- Low insertion loss
- Wide pass band
- High channel isolation
- High stability and reliability
- Epoxy free on optical path
- CWDM grid

Applications

- Broadband Systems
- Optical Add/Drop Multiplexing
- Metro/Access Communication
- Networks
- Fiber Optic Instruments

Product Overview

Parameter	Value
Center Wavelength	8ch CWDM ITU+ Exp. channel
Channel Spacing	20 nm
Channel Passband	±6.5 nm
Insertion Loss (CWDM. Port)	≤2.0dB

Information and specifications are subject to change without notice.
Please visit www.china-tscom.com for more information

8 Jinxiu Middle Road, Pingshan, Shenzhen, Guangdong, 518118, P. R. China
+86 755 32983688 | info@china-tscom.com | www.china-tscom.com



Insertion Loss (Exp. Port)	≤ 2.4 dB
Adjacent Channel Isolation	≥ 30 dB
Non-adjacent Channel Isolation	≥ 40 dB
Filter Technology	TFF (Thin Film Filter)
Passband Ripple	≤ 0.5 dB
Return Loss	≥ 45 dB
Directivity	≥ 50 dB
Polarization Dependent Loss	≤ 0.3 dB
Power Handling	≤ 300 mW
Operating Temperature	-40°C~ +85°C
Storage Temperature	-40°C~ +85°C
Fiber length	1.0-1.1m
Fiber Type	Corning G657A2
Pigtail and Connector Type	0.9mm loose tube with LC/UPC connector
Package Dimension	(L)54×(W)25×(H)7mm aluminum alloy box

Note: Losses above include connector loss and adapter loss.

