

9 Channels CCWDM Mux/Demux

Description

The adjacent channels of CCWDM use parallel beams to cascade in free space instead of using optical fibers. Without the fiber used in cascade, the size of CCWDM package can reach 54x25x7mm, which is about 3 times smaller than that of standard CWDM package.

CCWDM optical module is widely used in the fields of coarse wavelength division multiplexing system, PON network, CATV link, telecommunication network, enterprise network, metropolitan area network WDM system, 4G/5G communication mobile system, 100G solution, access network, metropolitan area network WDM system, optical fiber tools and so on.

Feature

- Low insertion loss
- Wide pass band
- High channel isolation
- High stability and reliability
- Epoxy free on optical path

Applications

- Broadband Systems
- Optical Add/Drop Multiplexing
- Metro/Access Communication
- Networks
- Fiber Optic Instruments

Product Overview

Parameter	Value
Center Wavelength	9ch CWDM ITU
Channel Spacing	20 nm
Channel Passband	±6.5 nm
Insertion Loss (CWDM Port)	≤2.0dB
Adjacent Channel Isolation	≥ 30 dB
Non-adjacent Channel Isolation	≥ 40 dB

Information and specifications are subject to change without notice.
Please visit www.china-tscom.com for more information

8 Jinxiu Middle Road, Pingshan, Shenzhen, Guangdong, 518118, P. R. China
+86 755 32983688 | info@china-tscom.com | www.china-tscom.com



Filter Technology	TFF (Thin Film Filter)
Passband Ripple	≤ 0.5 dB
Return Loss	≥ 45 dB
Directivity	≥ 50 dB
Polarization Dependent Loss	≤ 0.3 dB
Power Handling	≤ 300 mW
Operating Temperature	-40°C~ +85°C
Storage Temperature	-40°C~ +85°C
Fiber length	1.0 - 1.1m
Fiber Type	Corning G657A2
Pigtail and Connector Type	0.9mm loose tube with LC/UPC connector
Package Dimension	(L)54×(W)25×(H)7mm aluminum alloy box

Note: Losses above include connector loss and adapter loss.

